




YB1052/1052A High Frequency Signal Generator



Features:

- AM, FM and carrier frequency signal
- Digital technology such as SCM, digital potentiometer and etc;
- 5 digits frequency display
- Small waveform distribution, high frequency stability
- Auto, manual shift; AM, FM, internal & external modulation
- Audio frequency output
- Store or fetch ten work frequency and signal mode

Specifications	
Frequency Range	0.1MHz~150MHz
Output Amplitude	1.5Vp-p,amplitude(50Ω)
Output impedance	50Ω
Amplitude regulator	±2dB(>30MHz , ±0.5dB)
Output amplitude Adjustable	> 10dB
Output attenuation	-10dB,-20dB,-20dB,-20dB,Group(1052A)
AM Range	0~60%,continous
FM Shift	0~100kHz,Continous variable
Internal Module signal	1kHz,400Hz
External module range	20Hz~30kHz
External module input	< 5V
Audio Frequency	1kHz
Audio Output Amplitude	4Vrms
Audio distortion	< 1%
Audio output impedance	600Ω
Dimension	115H×270W×335D(mm)
Weight	Approx. 5.5kg



AM/ FM High Frequency Signal Generator

YB1052B High Frequency Signal Generator



Features:

- Frequency range 0.1~150 MHz
- 4 digits frequency display, 3 digit amplitude display
- AM, FM, internal & external modulation
- Audio frequency output 1kHz, 400 Hz
- High price performance ratio

Specifications	
Frequency Range	0.1MHz~150MHz
Audio frequency output amplitude	>1.5Vp-p, stable amplitude; (50 ohms)
INT AM	0~60% continuous to adjustable
INT FM offset	0~100kHz continuous to adjustable
INT modulation signal	1kHz, 400Hz
EXT modulation frequency	20 Hz ~ 10kHz
Dimension	100H×220W×300D (mm)
Weight	Approx. 3.5kg

CROMTECH INDIA

1st Floor Begum Niwas, Opp Mercantile, Bank Society Colony, 5th Natwar Nagar Road, Jogeshwari (East), Mumbai 400 060.

Maharashtra - India.

Mobile: +91 98693 82134 / 81088 13320

Telefax: +91 22 2838 6028

Email: cromamumbai@mail.com/ cromtechindia@mail.com/ info@cromtechindia.com/ sales@cromtechindia.com

Website: www.cromtechindia.com