

Digital Micro Voltmeter

- Very low temperature drift
- Low dc input bias current-10pA
- Measures voltage down to 1 μ V
- Automatic polarity indication
- Recorder facility (optional)



Features

Digital Micro voltmeter is a very versatile multipurpose instrument for the measurement of low dc voltage. It has 5 decade ranges from 1mV to 10V with 100% over-ranging. For better accuracy and convenience, readings are directly obtained on 3½ digit DPM (Digital Panel Meter).

This instrument uses a very well designed chopper stabilized IC amplifier. This amplifier offers exceptionally low offset voltage and input bias parameters, combined with excellent speed characteristics.

Filter circuit is provided to reduce the line pickups of 50Hz. All internal power supplies are IC regulated.

Applications

DC voltage measurements from high impedance sources; output of photomultiplier tubes, photocells, radiation detector etc.

Very low voltage measurement, direct measurement of thermo-couple output to read temperatures with a resolution of 1/40th of a degree (Chromel-Alumel).

General purpose laboratory instrument for voltages upto 19.99V DC. (Hall Effect, Four Probe, Thermo luminescence, Transistor and Diode characteristics etc.)

Specifications

Parameter	Value
Range	1mV, 10mV, 100mV, 1V & 10V with 100% over-ranging.
Resolution	1 μ V
Accuracy	$\pm 0.2\% \pm 1$ digit
Stability	Within ± 1 digit
Input Impedance	>1000M ohm (10Mohm on 10V range)
Display	3½ digit, 7 segment LED with auto polarity and decimal indication
Power Supply	220V $\pm 10\%$, 50Hz
Weight	2.5Kg
Dimensions	245mm X 280mm X 120mm

CROMTECH INDIA

1st Floor Begum Niwas, Opp Mercantile, Bank Society Colony, 5th Natwar Nagar Road, Jogeshwari (East), Mumbai 400 060.
Maharashtra - India.

Mobile: +91 98693 82134 / 81088 13320

Telefax: +91 22 2838 6028

Email: cromamumbai@mail.com / cromtechindia@mail.com / info@cromtechindia.com / sales@cromtechindia.com

Website: www.cromtechindia.com